

Content of List Modem Information.vbs (Site 1)

' Description: Retrieves information about all the modems installed in a computer.

On Error Resume Next

strComputer = "."

Set objWMIService = GetObject("winmgmts:"
& "(impersonationLevel=impersonate)!\" & strComputer & "\root\cimv2")

Set collItems = objWMIService.ExecQuery("Select * from Win32_POTSModem")

For Each objItem in collItems

```
Wscript.Echo "Attached To: " & objItem.AttachedTo
Wscript.Echo "Blind Off: " & objItem.BlindOff
Wscript.Echo "Blind On: " & objItem.BlindOn
Wscript.Echo "Compression Off: " & objItem.CompressionOff
Wscript.Echo "Compression On: " & objItem.CompressionOn
Wscript.Echo "Configuration Manager Error Code: " & _
    objItem.ConfigManagerErrorCode
Wscript.Echo "Configuration Manager User Configuration: " & _
    objItem.ConfigManagerUserConfig
Wscript.Echo "Configuration Dialog: " & objItem.ConfigurationDialog
Wscript.Echo "Country Selected: " & objItem.CountrySelected
Wscript.Echo "DCB: "
For Each objElement In objItem.DCB
    WScript.Echo vbTab & objElement
Next
Wscript.Echo "Default: "
For Each objElement In objItem.Default
    WScript.Echo vbTab & objElement
Next
Wscript.Echo "Device ID: " & objItem.DeviceID
Wscript.Echo "Device Type: " & objItem.DeviceType
Wscript.Echo "Driver Date: " & objItem.DriverDate
Wscript.Echo "Error Control Forced: " & objItem.ErrorControlForced
Wscript.Echo "Error Control Off: " & objItem.ErrorControlOff
Wscript.Echo "Error Control On: " & objItem.ErrorControlOn
Wscript.Echo "Flow Control Hard: " & objItem.FlowControlHard
Wscript.Echo "Flow Control Off: " & objItem.FlowControlOff
Wscript.Echo "Flow Control Soft: " & objItem.FlowControlSoft
Wscript.Echo "Inactivity Scale: " & objItem.InactivityScale
Wscript.Echo "Inactivity Timeout: " & objItem.InactivityTimeout
Wscript.Echo "Index: " & objItem.Index
Wscript.Echo "Maximum Baud Rate To SerialPort: " & _
    objItem.MaxBaudRateToSerialPort
Wscript.Echo "Model: " & objItem.Model
Wscript.Echo "Modem INF Path: " & objItem.ModemInfPath
Wscript.Echo "Modem INF Section: " & objItem.ModemInfSection
Wscript.Echo "Modulation Bell: " & objItem.ModulationBell
Wscript.Echo "Modulation CCITT: " & objItem.ModulationCCITT
Wscript.Echo "Name: " & objItem.Name
Wscript.Echo "PNP Device ID: " & objItem.PNPDeviceID
Wscript.Echo "Port SubClass: " & objItem.PortSubClass
Wscript.Echo "Prefix: " & objItem.Prefix
Wscript.Echo "Properties: "
For Each objElement In objItem.Properties
    WScript.Echo vbTab & objElement
Next
Wscript.Echo "Provider Name: " & objItem.ProviderName
Wscript.Echo "Pulse: " & objItem.Pulse
Wscript.Echo "Reset: " & objItem.Reset
Wscript.Echo "Responses Key Name: " & objItem.ResponsesKeyName
Wscript.Echo "Speaker Mode Dial: " & objItem.SpeakerModeDial
Wscript.Echo "Speaker Mode Off: " & objItem.SpeakerModeOff
Wscript.Echo "Speaker Mode On: " & objItem.SpeakerModeOn
Wscript.Echo "Speaker Mode Setup: " & objItem.SpeakerModeSetup
Wscript.Echo "Speaker Volume High: " & objItem.SpeakerVolumeHigh
Wscript.Echo "Speaker Volume Info: " & objItem.SpeakerVolumeInfo
Wscript.Echo "Speaker Volume Low: " & objItem.SpeakerVolumeLow
Wscript.Echo "Speaker Volume Med: " & objItem.SpeakerVolumeMed
Wscript.Echo "Status Info: " & objItem.StatusInfo
Wscript.Echo "Terminator: " & objItem.Terminator
Wscript.Echo "Tone: " & objItem.Tone
Wscript.Echo
Next
```